

SMEI Instrument Telemetry Format Specification

M.P.Cooke

and

C.J.Eyles

University of Birmingham

Issue 7

15 November 2004

Table of Contents

1. Introduction	3
1.1 Nomenclature	3
2. Data Sources	3
2.1 State of Health Information	3
2.2 Camera Image Information	3
2.3 Spacecraft Time and Attitude Information	3
3. SMEI to Spacecraft Data Streams	4
3.1 State Of Health Stream	4
3.1.1 Camera Observation Parameters	4
3.1.2 Analogue and Digital Monitors	5
3.1.3 Flat Field Table Checksums	8
3.1.4 Command / Instrument Status Return	8
3.1.5 Single Event Upset Information	10
3.1.6 Paged Region Memory Dump	10
3.1.7 Fixed Region Memory Dump	11
3.1.8 Software Performance Counters	11
3.1.9 Housekeeping Test Pattern	12
3.1.10 Spacecraft Time and Attitude Parameters	12
3.1.11 Reserved Blocks	12
3.2 Science Data Stream	14
3.2.1 Science Data Stream Synchronisation Header	14
3.2.2 Image Data Packet Format	14
A. Rectangular Error Correction Coding	16
A.1 SMEI Conventions	16
B. Housekeeping Checksum Coding	17
C. Rice Compression Coding	18
D. Analogue Monitor Calibration Tables	19

1. Introduction

The SMEI instrument routinely accumulates science and housekeeping data while it is operating. This document defines the formats and protocols used when transferring this data to the spacecraft.

This document does not cover instrument commanding, which is detailed in the 'SMEI Instrument Commanding Protocol' (SMEI/UB/SPE/001), and the 'SMEI Instrument Commanding Specification' (SMEI/UB/SPE/002).

This document applies to SMEI Software revision 34 and later.

1.1 Nomenclature

The general format used for presenting data is a sequence of 16-bit words with a mask indicating which bits are valid and invalid for each parameter. The most significant bit is shown at the left, the least significant bit at the right of the mask field.

Where a parameter is shown as a field with a number of options, unspecified options are not permitted.

Examples:

Word	Mask	Parameter
0	xxxxxxxxxxxxxxxxxxxx	All bits are valid.
1	xxxxxxxx- - - - -	Bits 15 -8 are valid.
2	- - - - -xxxxxxxx	Bits 7 -0 are valid.
3	- - - - -x- - - - -	Bit 7 is valid. Eg, 0=Disabled, 1=Enabled.
4	- - - - -xxxxxxxx	8 LSBs of parameter A
5	- - - - -xxx- -	Bits 4-2 are valid and the meaning is dependant on the sub-mask
	- - - - -000- -	option 0
	- - - - -001- -	option 1
	- - - - -010- -	option 2
6	- - - - - - - - -1	Bit 0 is always 1
7-31		These words are not applicable, or are described elsewhere.

2. Data Sources

Science image data and telemetry are routinely accumulated into blocks and stored in the main memory of the data handling unit (DHU). During standard operations, these blocks of data are transmitted to the spacecraft continuously over the MIL-STD-1553B bus. There is no provision onboard SMEI for long term storage of more than a few images.

2.1 State of Health Information

Instrument housekeeping data is grouped into 32-word packets as it is collected. As SMEI produces more than 32 words of housekeeping data, each packet has a type identifier, so we can de-multiplex the data during ground processing. Each state of health packet is time-stamped using the least significant seconds field received from the spacecraft.

2.2 Camera Image Information

SMEI images are (optionally) compressed and error correction encoded by the DHU. Each image is broken into a number of 256-word units of (compressed) data, though the final unit of data for an image is usually smaller than this. Eight words of error correction codes are prefixed to each unit to make an image data packet.

2.3 Spacecraft Time and Attitude Information

The spacecraft provides periodic updates of the current time and the attitude data for the payload. The interface is defined in section C6.2.1 of the Interface Control Document (ICD).

3. SMEI to Spacecraft Data Streams

The SMEI DHU is designed to produce two logical streams of data for the spacecraft. The first is a State of Health (SoH) stream, of 2560 bits per second. This is simply composed of instrument housekeeping packets.

The second stream is the Science Data Stream (SDS), of 64,000 bits per second in normal operating mode, and 128,000 bits per second in engineering mode. This stream is composed of both camera image data, and instrument housekeeping. Appropriate synchronisation header information is included in the data stream to separate the two.

3.1 State Of Health Stream

The generic format of the SoH packet is shown below. It uses a 3 word fixed format header, containing a housekeeping identifier, checksum and timestamp.

The type identifier uses a single bit to identify the type of housekeeping contained in the packet. This leaves four spare identifiers for later additions.

The cyclic redundancy check is generated using the same scheme as WindSat . The details can be found in Appendix C.

The timestamp field is just a copy of the least significant word of the spacecraft time seconds data (SCT Seconds LSW) that the spacecraft supplies to SMEI 5 times per second. This allows good knowledge of when the housekeeping was last updated, image exposures started and so forth. Spacecraft time is currently defined as time since noon 1/1/2000 UTC, though this is still to be confirmed.

Word	Mask	Mnemonic	Parameter
0	xxxxxxxxxxxxxxxxxxxx 0000000000000001 0000000000000010 0000000000000011 0000000000000100 0000000000000101 0000000000000110 0000000000000111 0000000000001000 0000000000001001 0000000000001010 0000000000001011 0000000000001100 0000000000001101 0000000000001110 0000000000001111 xxxxxxxxxxxxx0000	SOH_TYPE	Multiplex Packet Type Identifier Spare Block Spare Block Spare Block Camera 1 Observation Parameters Camera 2 Observation Parameters Camera 3 Observation Parameters Analogue and Digital Monitors Flat Field Table Checksums Command Status Return Single Event Upset Information Paged Region Memory Dump Fixed Region Memory Dump Software Performance Counters Housekeeping Test Pattern Spacecraft Time and Attitude Parameters Spare Blocks
1	xxxxxxxxxxxxxxxxxxxx	SOH_CRC	Cyclic Redundancy Check (16-bit SDLC CRC)
2	xxxxxxxxxxxxxxxxxxxx	SOH_TIME	Time-stamp of the last update of this data packet
3-31			Variable packet data dependant on the type identifier

3.1.1 Camera Observation Parameters

During normal observation modes, a number of bins from each image are sampled, and stored in these housekeeping packets - one for each camera. This allows a quick-look facility to monitor the CCD performance without needing to fully decode the science data stream. Also in this housekeeping packet are 'critical observation parameters', which are used when decoding each image.

Word	Mask	Mnemonic	Parameter
0	000000000000xxxx 0000000000000100 0000000000000101 0000000000000110	SOH_TYPE	Camera Observation Parameters Camera 1 Camera 2 Camera 3
1	xxxxxxxxxxxxxxxxxxxx	SOH_CRC	Cyclic Redundancy Check
2	xxxxxxxxxxxxxxxxxxxx	SOH_TIME _x	Time-stamp of the last update (x = 4/5/6)
3	xxxxxxxxxxxxxxxxxxxx	OBS_FRAME	Observation Frame Number
4	xxxxxxxx- - - - -	OBS_INTV	Frame Period (seconds)
4	- - - - - 00000100	OBS_EXP	Frame Exposure Time (seconds)

5	-----xxxxxxxx	OBS_MODE	Observation mode
	-----00000000		Engineering mode
	-----00000001		High Resolution Mode
	-----00000010		Normal Mode
	-----00000011		Camera On, No Data Acquisition Mode
			Any other value - camera disabled
5	xxxxxxxx-----		Spare
6	-----x	RICE_EN	Rice Compression Enable (1 = Enabled)
6	-----0-	RICE_DT	Rice Compression Delta Coding Enable (Always On)
6	-----x-	FLAT_EN	Flat Field Correction Enabled (1 = Enabled)
6	-----x-	FF_LED_EN	Flat Field Led Enabled (1 = Switched On)
6	-----x-	ST_ASAP	Resume Frame Store Immediately (1 = Immediate)
6	xxxxxxxxxxxx-		Spare (0)
7	-----xxxx	ROI_MAP	Region Of Interest Map
	-----0000		Minimal Region Of Interest
	-----0001		Full CCD Region Of Interest
	-----0010		UCSD Region Of Interest
	-----0011		EMC Stripe Test Region Of Interest
	-----0100		UCSD Region Of Interest (2 nd Copy)
7	xxxxxxxxxxxx-		Spare (0)
8	xxxxxxxxxxxxxxxx	CCD_SKIP	CCD Row Skip Count
9	xxxxxxxxxxxxxxxx	MTR_OPEN	Shutter Open Command
	-----xxxx	MO_PHASE	Phase to power (1 = P0, 2 = P1, 4 = P2, 8 = P3)
	-----xxxx-	MO_CAM	Camera Identifier (1 = Cam1, 2 = Cam2, 3 = Cam3)
	----xxxx-	MO_PWR	Phase Energise Time (seconds)
	xxxx-	MO_SETTLE	Phase Settle Time (seconds. Valid range 1-15)
10	xxxxxxxxxxxxxxxx	RECAL_INT	Frames Between Recalibrations (0 = no recalibration)
11	xxxxxxxx-	RICE_KMAX	Rice Encoding Kmax
11	-----xxxxxxxx	RICE_N	Rice Encoding Noise Bits
12	xxxxxxxxxxxxxxxx	MTR_CLOSE	Shutter Closed Command
	-----xxxx	MC_PHASE	Phase to power (1 = P0, 2 = P1, 4 = P2, 8 = P3)
	-----xxxx-	MC_CAM	Camera Identifier (1 = Cam1, 2 = Cam2, 3 = Cam3)
	----xxxx-	MC_PWR	Phase Energise Time (seconds)
	xxxx-	MC_SETTLE	Phase Settle Time (seconds. Valid range 1-15)
13	xxxxxxxxxxxxxxxx	FF_SCALE	Flat Field Prescaler
14	-----x-	BOS_ALERT	Bright Object Sensor Alert (1 = Alert State)
14	-----xxx	BOS_CNTR	Bright Object State Change Counter (0-5)
15	xxxxxxxxxxxxxxxx	OBS_FR_OK	Frames Completed Without Errors Count
16	xxxxxxxxxxxxxxxx	CCD_BIN0	CCD Bin 0
17	xxxxxxxxxxxxxxxx	CCD_BIN1	CCD Bin 1
18	xxxxxxxxxxxxxxxx	CCD_BIN2	CCD Bin 2
19	xxxxxxxxxxxxxxxx	CCD_BIN3	CCD Bin 3
20	xxxxxxxxxxxxxxxx	CCD_BIN4	CCD Bin 4
21	xxxxxxxxxxxxxxxx	CCD_BIN5	CCD Bin 5
22	xxxxxxxxxxxxxxxx	CCD_BIN6	CCD Bin 6
23	xxxxxxxxxxxxxxxx	CCD_BIN7	CCD Bin 7
24	xxxxxxxxxxxxxxxx	CCD_BIN8	CCD Bin 8
25	xxxxxxxxxxxxxxxx	CCD_BIN9	CCD Bin 9
26	xxxxxxxxxxxxxxxx	CCD_BIN10	CCD Bin 10
27	xxxxxxxxxxxxxxxx	CCD_BIN11	CCD Bin 11
28	xxxxxxxxxxxxxxxx	CCD_BIN12	CCD Bin 12
29	xxxxxxxxxxxxxxxx	CCD_BIN13	CCD Bin 13
30	xxxxxxxxxxxxxxxx	CCD_BIN14	CCD Bin 14
31	xxxxxxxxxxxxxxxx	CCD_BIN15	CCD Bin 15

3.1.2 Analogue and Digital Monitors

- The analogue monitoring on SMEI is done using an 8-bit ADC
- See Appendix D for analogue monitor calibration factors.

Word	Mask	Mnemonic	Parameter
0	0000000000000111	SOH_TYPE	Analogue and Digital Monitors
1	xxxxxxxxxxxxxxxxxxxx	SOH_CRC	Cyclic Redundancy Check
2	xxxxxxxxxxxxxxxxxxxx	SOH_TIME7	Time-stamp of the last update of this data packet
3	xxxxxxxx- - - - -	AM_SUPP_I	AMon 0 : SMEI Current Monitor
3	- - - - - xxxxxxxxxxx	AM_DHU_5V	AMon 1 : Main DHU 5V supply
4	xxxxxxxx- - - - -	AM_PROC_T	AMon 2 : Processor temperature monitor
4	- - - - - xxxxxxxxxxx	AM_PSU_T	AMon 3 : Power supply temperature monitor
5	xxxxxxxx- - - - -	AM_SPARE	AMon 4 : Spare Analogue Monitor
5	- - - - - xxxxxxxxxxx	AM_PROC_I	AMon 5 : Processor current monitor
6	xxxxxxxx- - - - -	AM_C1RAD_T	AMon 6 : Camera 1 Radiator Temperature
6	- - - - - xxxxxxxxxxx	AM_C1CCD_T	AMon 7 : Camera 1 CCD Temperature
7	xxxxxxxx- - - - -	AM_C1EL_T	AMon 8 : Camera 1 Electronics Temperature
7	- - - - - xxxxxxxxxxx	AM_C1MIR_T	AMon 9 : Camera 1 Mirror Temperature
8	xxxxxxxx- - - - -	AM_C1BAF_T	AMon 10 : Camera 1 Baffle Temperature
8	- - - - - xxxxxxxxxxx	AM_C1SPR_T	AMon 11 : Camera 1 Spare Temperature Monitor
9	xxxxxxxx- - - - -	AM_C2RAD_T	AMon 12 : Camera 2 Radiator Temperature
9	- - - - - xxxxxxxxxxx	AM_C2CCD_T	AMon 13 : Camera 2 CCD Temperature
10	xxxxxxxx- - - - -	AM_C2EL_T	AMon 14 : Camera 2 Electronics Temperature
10	- - - - - xxxxxxxxxxx	AM_C2MIR_T	AMon 15 : Camera 2 Mirror Temperature
11	xxxxxxxx- - - - -	AM_C2BAF_T	AMon 16 : Camera 2 Baffle Temperature
11	- - - - - xxxxxxxxxxx	AM_C2SPR_T	AMon 17 : Camera 2 Spare Temperature Monitor
12	xxxxxxxx- - - - -	AM_C3RAD_T	AMon 18 : Camera 3 Radiator Temperature
12	- - - - - xxxxxxxxxxx	AM_C3CCD_T	AMon 19 : Camera 3 CCD Temperature
13	xxxxxxxx- - - - -	AM_C3EL_T	AMon 20 : Camera 3 Electronics Temperature
13	- - - - - xxxxxxxxxxx	AM_C3MIR_T	AMon 21 : Camera 3 Mirror Temperature
14	xxxxxxxx- - - - -	AM_C3BAF_T	AMon 22 : Camera 3 Baffle Temperature
14	- - - - - xxxxxxxxxxx	AM_C3SPR_T	AMon 23 : Camera 3 Spare Temperature Monitor
15	xxxxxxxxxxxxxxxxxxxx		Digital Monitors 0
	- - - - - xxxxxxxxxxx	ADC_RB	ADC Conversion Value
	- - - xxxxx- - - - -	ADC_MUX	ADC Multiplexer
	- - x- - - - - - - -	ADC_WR	ADC WR Line Status
	- x- - - - - - - - -	E2PROM_WEN	E ² Prom Write Enable
	x- - - - - - - - - -	WDOG_EN	Watchdog Enable
16	xxxxxxxxxxxxxxxxxxxx		Digital Monitors 1
	- - - - - - - - - - x	C1_SHT_OPN	Camera 1 Shutter (1 = Open)
	- - - - - - - - - - x-	C1_DOR_CLS	Camera 1 Door (1 = Closed)
	- - - - - - - - - - x-	C2_SHT_OPN	Camera 2 Shutter (1 = Open)
	- - - - - - - - - - x-	C2_DOR_CLS	Camera 2 Door (1 = Closed)
	- - - - - - - - - - x-	C3_SHT_OPN	Camera 3 Shutter (1 = Open)
	- - - - - - - - - - x-	C3_DOR_CLS	Camera 3 Door (1 = Closed)
	- - - - - - - - - - x-	C1_BOS_SUN	Camera 1 Bright Object Sensor (1 = Sun in view)
	- - - - - - - - - - x-	C2_BOS_SUN	Camera 2 Bright Object Sensor (1 = Sun in view)
	- - - - - - - - - - x-	C3_BOS_SUN	Camera 3 Bright Object Sensor (1 = Sun in view)
	- - - - - - - - - - x-	C3_1HZ	1Hz Monitor
	- - - xxx- - - - - -	CODE_VER	E2Prom Software Boot Code Identifier
	- - x- - - - - - - -		Repeat of BANK1_SEL, bit 5
	- x- - - - - - - - -	BOOT_RES	Boot Res
	x- - - - - - - - - -	IRQ4	Interrupt 4
17	xxxxxxxxxxxxxxxxxxxx		Digital Monitors 2
	- - - - - - - - - - xxxxxxx	BANK0_SEL	16K Memory Bank 0 Selector
	- - - - - - - - - - x-		Spare
	- xxxxxxx- - - - -	BANK1_SEL	16K Memory Bank 1 Selector
	x- - - - - - - - - -	AB_IDENT	A/B Processor Identifier
18	xxxxxxxxxxxxxxxxxxxx		Digital Monitors 3
	- xxxxxxxxxxxxxxxxxxx		Spare
	x- - - - - - - - - -	AC_PARITY	FPGA 16-bit Parity Generator
19	xxxxxxxxxxxxxxxxxxxx		Digital Monitors 4
	- - - - - - - - - - - x	C1_PHASE_0	Camera 1 Shutter Phase 0 (Closed, No FF)
	- - - - - - - - - - - x-	C1_PHASE_1	Camera 1 Shutter Phase 1 (Open, Hall B)

	-----x--	C1_PHASE_2	Camera 1 Shutter Phase 2 (Closed, FF)
	-----x--	C1_PHASE_3	Camera 1 Shutter Phase 3 (Open, Hall A)
	-----x--	C1_ON	Camera 1 On (FET control)
	-----x--	C1_SPARE1	Camera 1 Spare
	-----x--	C1_DEI_ON	Camera 1 De-ice Heater On
	-----x--	C1_HOP_ON	Camera 1 HOP On
	-----x--	C1_RLY_ON	Camera 1 Power Relay Coil Monitor
	-----x--	C1_SDA_IN	Camera 1 SDA In Monitor
	-----x--	C1_INT	Camera 1 Interrupt Status Monitor
	-----x--	C1_OVF	Camera 1 Hardware FIFO Overflow
	-----x--	C1_HOP_EN	Camera 1 HOP Protection Status
	-----x--	C1_SPARE2	Camera 1 Spare
	-----x--	C1_SPARE3	Camera 1 Spare
	-----x--	C1_LED_ON	Camera 1 LED On
20	xxxxxxxxxxxxxxxxxxxx		Digital Monitors 5
	-----x--	C2_PHASE_0	Camera 2 Shutter Phase 0 (Closed, No FF)
	-----x--	C2_PHASE_1	Camera 2 Shutter Phase 1 (Open, Hall B)
	-----x--	C2_PHASE_2	Camera 2 Shutter Phase 2 (Closed, FF)
	-----x--	C2_PHASE_3	Camera 2 Shutter Phase 3 (Open, Hall A)
	-----x--	C2_ON	Camera 2 On (FET control)
	-----x--	C2_SPARE1	Camera 2 Spare
	-----x--	C2_DEI_ON	Camera 2 De-ice Heater On
	-----x--	C2_HOP_ON	Camera 2 HOP On
	-----x--	C2_RLY_ON	Camera 2 Power Relay Coil Monitor
	-----x--	C2_SDA_IN	Camera 2 SDA In Monitor
	-----x--	C2_INT	Camera 2 Interrupt Status Monitor
	-----x--	C2_OVF	Camera 2 Hardware FIFO Overflow
	-----x--	C2_HOP_EN	Camera 2 HOP Protection Monitor
	-----x--	C2_SPARE2	Camera 2 Spare
	-----x--	C2_SPARE3	Camera 2 Spare
	-----x--	C2_LED_EN	Camera 2 LED On
21	xxxxxxxxxxxxxxxxxxxx		Digital Monitors 6
	-----x--	C3_PHASE_0	Camera 3 Shutter Phase 0 (Closed, No FF)
	-----x--	C3_PHASE_1	Camera 3 Shutter Phase 1 (Open, Hall B)
	-----x--	C3_PHASE_2	Camera 3 Shutter Phase 2 (Closed, FF)
	-----x--	C3_PHASE_3	Camera 3 Shutter Phase 3 (Open, Hall A)
	-----x--	C3_ON	Camera 3 On
	-----x--	C3_SPARE1	Camera 3 Spare
	-----x--	C3_DEI_ON	Camera 3 De-ice Heater On
	-----x--	C3_HOP_ON	Camera 3 HOP On
	-----x--	C3_RLY_ON	Camera 3 Power Relay Coil Monitor
	-----x--	C3_SDA_IN	Camera 3 SDA In Monitor
	-----x--	C3_INT	Camera 3 Interrupt Status Monitor
	-----x--	C3_OVF	Camera 3 Hardware FIFO Overflow
	-----x--	C3_HOP_EN	Camera 3 HOP Protection Monitor
	-----x--	C3_SPARE2	Camera 3 Spare
	-----x--	C3_SPARE3	Camera 3 Spare
	-----x--	C3_LED_ON	Camera 3 LED On
22	xxxxxxxxxxxxxxxxxxxx		Digital Monitors 7
	-----xxxxx	WDOG_MSB	Watchdog Timer Eradicable
	-----000		Spare
	-----x--	OBS_STAT	Current observing status
	-----x--	AB_1553	1553 A / B side selection status
	-----x--	HOT_START	Hot start status
	-----x--	WARM_START	Warm start status
	-----x--	1553_SSFLG	1553 SSFlag
	-----x--	1553_INCMD	1553 In Command
	-----x--	1553_MEMEN	1553 Memory Enable
	-----x--	1553_RDYD	1553 ReadyD
23	xxxxxxxxxxxxxxxxxxxx		Alignment padding (0)

24	-----xxxx	C1_LSTPH	Camera 1 Last shutter phase powered
25	-----xxxx	C2_LSTPH	Camera 2 Last shutter phase powered
26	-----xxxx	C3_LSTPH	Camera 3 Last shutter phase powered
27	xxxxxxxx-----	CMD_SEQ_NUM	Command Sequence Number
28-29	xxxxxxxxxxxxxxxx		Spare (0)
30	xxxxxxxxxxxxxxxx	I2C_TIMER	Timeout counter until I2C state is considered frozen
31	xxxxxxxxxxxxxxxx	EOF_TIMER	Timeout counter since last end-of-frame was detected

3.1.3 Flat Field Table Checksums

The flat field tables used during camera data processing are periodically checked for single event errors using a simple xor-based checksum. The 16-bit checksums are returned in this packet.

Word	Mask	Mnemonic	Parameter
0	0000000000001000	SOH_TYPE	Flat Field Table Checksums
1	xxxxxxxxxxxxxxxx	SOH_CRC	Cyclic Redundancy Check
2	xxxxxxxxxxxxxxxx	SOH_TIME8	Time-stamp of the last update of this data packet
3	xxxxxxxxxxxxxxxx	CSUM_BLK0	Camera 1 Flat Field Table Page 0
4	xxxxxxxxxxxxxxxx	CSUM_BLK1	Camera 1 Flat Field Table Page 1
5	xxxxxxxxxxxxxxxx	CSUM_BLK2	Camera 1 Flat Field Table Page 2
6	xxxxxxxxxxxxxxxx	CSUM_BLK3	Camera 1 Flat Field Table Page 3
7	xxxxxxxxxxxxxxxx	CSUM_BLK4	Camera 1 Flat Field Table Page 4
8	xxxxxxxxxxxxxxxx	CSUM_BLK5	Camera 1 Flat Field Table Page 5
9	xxxxxxxxxxxxxxxx	CSUM_BLK6	Camera 1 Flat Field Table Page 6
10	xxxxxxxxxxxxxxxx	CSUM_BLK7	Camera 1 Flat Field Table Page 7
11	xxxxxxxxxxxxxxxx	CSUM_BLK8	Camera 2 Flat Field Table Page 0
12	xxxxxxxxxxxxxxxx	CSUM_BLK9	Camera 2 Flat Field Table Page 1
13	xxxxxxxxxxxxxxxx	CSUM_BLK10	Camera 2 Flat Field Table Page 2
14	xxxxxxxxxxxxxxxx	CSUM_BLK11	Camera 2 Flat Field Table Page 3
15	xxxxxxxxxxxxxxxx	CSUM_BLK12	Camera 2 Flat Field Table Page 4
16	xxxxxxxxxxxxxxxx	CSUM_BLK13	Camera 2 Flat Field Table Page 5
17	xxxxxxxxxxxxxxxx	CSUM_BLK14	Camera 2 Flat Field Table Page 6
18	xxxxxxxxxxxxxxxx	CSUM_BLK15	Camera 2 Flat Field Table Page 7
19	xxxxxxxxxxxxxxxx	CSUM_BLK16	Camera 3 Flat Field Table Page 0
20	xxxxxxxxxxxxxxxx	CSUM_BLK17	Camera 3 Flat Field Table Page 1
21	xxxxxxxxxxxxxxxx	CSUM_BLK18	Camera 3 Flat Field Table Page 2
22	xxxxxxxxxxxxxxxx	CSUM_BLK19	Camera 3 Flat Field Table Page 3
23	xxxxxxxxxxxxxxxx	CSUM_BLK20	Camera 3 Flat Field Table Page 4
24	xxxxxxxxxxxxxxxx	CSUM_BLK21	Camera 3 Flat Field Table Page 5
25	xxxxxxxxxxxxxxxx	CSUM_BLK22	Camera 3 Flat Field Table Page 6
26	xxxxxxxxxxxxxxxx	CSUM_BLK23	Camera 3 Flat Field Table Page 7
27	xxxxxxxxxxxxxxxx	CSUM_BLK24	Command Tables, 1553 Setup Table (#1), ROI Maps
28	xxxxxxxxxxxxxxxx	CSUM_BLK25	Camera ASIC Tables
29	xxxxxxxxxxxxxxxx	CSUM_BLK26	Uploaded Software Image
30	xxxxxxxxxxxxxxxx	CSUM_BLK27	Predefined Camera Configuration Tables
31	xxxxxxxxxxxxxxxx	CSUM_BLK28	1553 Setup Table (#2)

3.1.4 Command / Instrument Status Return

All 1553 messages received by SMEI on subaddresses 4 and 5 have status information returned in this packet. The table is filled in a cyclic fashion, and a counter identifies the last filled entry. The SMEI global configuration word and mode are also returned in this packet.

Word	Mask	Mnemonic	Parameter
0	0000000000001001	SOH_TYPE	Command Status Return
1	xxxxxxxxxxxxxxxx	SOH_CRC	Cyclic Redundancy Check
2	xxxxxxxxxxxxxxxx	SOH_TIME9	Time-stamp of the last update of this data packet
3	xxxxxxx-----	CMD_ACP	Total number of valid commands accepted
3	-----xxxxxxx	CMD_REJ	Total number of invalid commands rejected
4	-----0xxxxxxx	SOH_TOT	Total number of SOH requests serviced
4	0xxxxxxx-----	ERR_TOT	Total number of 1553 hybrid message errors detected
5	xxxxxxxxxxxxxxxx	SCI_TOT	Total number of science data requests serviced

The command identifier uniquely identifies the command type, and the checksum is used to distinguish individual commands.

The status word provides details of the actions SMEI took in response to the command.

The last eight commands which were received are stored in CMDx_ID/CS/ST. This array is treated as a circular buffer, and CMD_LAST indicates the most recently filled entry, ie x.

3.1.5 Single Event Upset Information

SMEI has regions of memory allocated for three copies of critical instrument parameters and switches. These areas are routinely monitored for single event upsets by mutual-comparison, and information about any anomalies found are reported in this housekeeping block. SMEI uses per-bit correction, and therefore a value can never be unable to be corrected, as at least two of the three bits will always match. The array is treated as a circular buffer, and TRM_LAST indicates the most recently filled entry in the array.

Word	Mask	Mnemonic	Parameter
0	0000000000001010	SOH_TYPE	Single event upset information
1	xxxxxxxxxxxxxxxxxxxx	SOH_CRC	Cyclic Redundancy Check
2	xxxxxxxxxxxxxxxxxxxx	SOH_TIME10	Time-stamp of the last update of this data packet
3	xxxxxxxxxxxxxxxxxxxx	TRM_CERR	Total number of correctable upsets recorded
4	xxxxxxxxxx		Spare
4	-----0000xxxx	TRM_LAST	Number of last entry filled (0-8)
5	xxxxxxxxxxxxxxxxxxxx	TRM0_ADDR	#0 Address
6	xxxxxxxxxxxxxxxxxxxx	TRM0_TS	#0 Time-stamp
7	xxxxxxxxxxxxxxxxxxxx	TRM0_RV	#0 Replacement Value
8	xxxxxxxxxxxxxxxxxxxx	TRM1_ADDR	#1 Address
9	xxxxxxxxxxxxxxxxxxxx	TRM1_TS	#1 Time-stamp
10	xxxxxxxxxxxxxxxxxxxx	TRM1_RV	#1 Replacement Value
11	xxxxxxxxxxxxxxxxxxxx	TRM2_ADDR	#2 Address
12	xxxxxxxxxxxxxxxxxxxx	TRM2_TS	#2 Time-stamp
13	xxxxxxxxxxxxxxxxxxxx	TRM2_RV	#2 Replacement Value
14	xxxxxxxxxxxxxxxxxxxx	TRM3_ADDR	#3 Address
15	xxxxxxxxxxxxxxxxxxxx	TRM3_TS	#3 Time-stamp
16	xxxxxxxxxxxxxxxxxxxx	TRM3_RV	#3 Replacement Value
17	xxxxxxxxxxxxxxxxxxxx	TRM4_ADDR	#4 Address
18	xxxxxxxxxxxxxxxxxxxx	TRM4_TS	#4 Time-stamp
19	xxxxxxxxxxxxxxxxxxxx	TRM4_RV	#4 Replacement Value
20	xxxxxxxxxxxxxxxxxxxx	TRM5_ADDR	#5 Address
21	xxxxxxxxxxxxxxxxxxxx	TRM5_TS	#5 Time-stamp
22	xxxxxxxxxxxxxxxxxxxx	TRM5_RV	#5 Replacement Value
23	xxxxxxxxxxxxxxxxxxxx	TRM6_ADDR	#6 Address
24	xxxxxxxxxxxxxxxxxxxx	TRM6_TS	#6 Time-stamp
25	xxxxxxxxxxxxxxxxxxxx	TRM6_RV	#6 Replacement Value
26	xxxxxxxxxxxxxxxxxxxx	TRM7_ADDR	#7 Address
27	xxxxxxxxxxxxxxxxxxxx	TRM7_TS	#7 Time-stamp
28	xxxxxxxxxxxxxxxxxxxx	TRM7_RV	#7 Replacement Value
29	xxxxxxxxxxxxxxxxxxxx	TRM8_ADDR	#8 Address
30	xxxxxxxxxxxxxxxxxxxx	TRM8_TS	#8 Time-stamp
31	xxxxxxxxxxxxxxxxxxxx	TRM8_RV	#8 Replacement Value

3.1.6 Paged Region Memory Dump

This is a simple sliding dump of the contents of the E²Prom and bulk storage SRAM. This allows a slow-scan picture of the current state of the entire SMEI memory to be built. Single bit errors can be located and corrected via patching as required.

Word	Mask	Mnemonic	Parameter
0	0000000000001011	SOH_TYPE	Paged Region Memory Dump
1	xxxxxxxxxxxxxxxxxxxx	SOH_CRC	Cyclic Redundancy Check
2	xxxxxxxxxxxxxxxxxxxx	SOH_TIME11	Time-stamp of the last update of this data packet
3	xxxxxxxx-----		Spare

3	-----0xxxxxxx	MEM_PAGE	Page selector
4	00xxxxxxxxxxxxxxxx	MEM_OFFSET	Page start offset (0 - 3FE5h)
5-31	xxxxxxxxxxxxxxxx	MEM_DATA	Memory dump

3.1.7 Fixed Region Memory Dump

This is a simple sliding dump of the contents of the processor RAM. This allows a slow-scan picture of the current state of the memory to be built. Single bit errors can be located and potentially corrected for during science data processing.

Word	Mask	Mnemonic	Parameter
0	0000000000001100	SOH_TYPE	Fixed Memory Dump
1	xxxxxxxxxxxxxxxx	SOH_CRC	Cyclic Redundancy Check
2	xxxxxxxxxxxxxxxx	SOH_TIME12	Time-stamp of the last update of this data packet
3	0xxxxxxxxxxxxxxxx	FIX_OFFSET	Page start offset (0 - 7FE4h)
4-31	xxxxxxxxxxxxxxxx	FIX_DATA	Memory dump

3.1.8 Software Performance Counters

The onboard software has a number of performance counters built in, which allow bottlenecks to be detected.

Word	Mask	Mnemonic	Parameter
0	0000000000001101	SOH_TYPE	Software Performance Counters
1	xxxxxxxxxxxxxxxx	SOH_CRC	Cyclic Redundancy Check
2	xxxxxxxxxxxxxxxx	SOH_TIME13	Time-stamp of the last update of this data packet
3	xxxxxxxxxxxxxxxx	C1_IRB_SIZE	Camera 1 Interrupt Ring Buffer size
4	xxxxxxxxxxxxxxxx	C1_IRB_MF	Camera 1 Interrupt Ring Buffer maximum fill
5	xxxxxxxxxxxxxxxx	C1_IRB_OVF	Camera 1 Interrupt Ring Buffer overflows
6	xxxxxxxxxxxxxxxx	C1_FRM_ST	Camera 1 I2C Frame Starts Issued
7	xxxxxxxxxxxxxxxx	C1_FRM_EOF	Camera 1 End of Frame Data reached
8	xxxxxxxxxxxxxxxx	C1_TLM_FULL	Camera 1 Telemetry Buffer Full Conditions
9	xxxxxxxxxxxxxxxx	C1_TLM_FREE	Camera 1 Free 64K Telemetry Pages
10	xxxxxxxxxxxxxxxx	C1_DEICE_CNT	Camera 1 Deice Heater Countdown
11	xxxxxxxxxxxxxxxx	C2_IRB_SIZE	Camera 2 Interrupt Ring Buffer size
12	xxxxxxxxxxxxxxxx	C2_IRB_MF	Camera 2 Interrupt Ring Buffer maximum fill
13	xxxxxxxxxxxxxxxx	C2_IRB_OVF	Camera 2 Interrupt Ring Buffer overflows
14	xxxxxxxxxxxxxxxx	C2_FRM_ST	Camera 2 I2C Frame Starts Issued
15	xxxxxxxxxxxxxxxx	C2_FRM_EOF	Camera 2 End of Frame Data reached
16	xxxxxxxxxxxxxxxx	C2_TLM_FULL	Camera 2 Telemetry Buffer Full Conditions
17	xxxxxxxxxxxxxxxx	C2_TLM_FREE	Camera 2 Free 64K Telemetry Pages
18	xxxxxxxxxxxxxxxx	C2_DEICE_CNT	Camera 2 Deice Heater Countdown
19	xxxxxxxxxxxxxxxx	C3_IRB_SIZE	Camera 3 Interrupt Ring Buffer size
20	xxxxxxxxxxxxxxxx	C3_IRB_MF	Camera 3 Interrupt Ring Buffer maximum fill
21	xxxxxxxxxxxxxxxx	C3_IRB_OVF	Camera 3 Interrupt Ring Buffer overflows
22	xxxxxxxxxxxxxxxx	C3_FRM_ST	Camera 3 I2C Frame Starts Issued
23	xxxxxxxxxxxxxxxx	C3_FRM_EOF	Camera 3 End of Frame Data reached
24	xxxxxxxxxxxxxxxx	C3_TLM_FULL	Camera 3 Telemetry Buffer Full Conditions
25	xxxxxxxxxxxxxxxx	C3_TLM_FREE	Camera 3 Free 64K Telemetry Pages
26	xxxxxxxxxxxxxxxx	C3_DEICE_CNT	Camera 3 Deice Heater Countdown
27	xxxxxxxxxxxxxxxx	REBOOT_CNT	Software Reboot Counter
28	-xxxxxxxxxxxxxxxx	SW_REL	Bootstrap Software Revision
28	x-----	FM_DHU	FM DHU Indicator (1 = FM, 0 = EM)
29	-----xxxxxxxx	CNT_1HZ	1Hz Interrupts Processed
29	xxxxxxx-----	SIM_1HZ	1Hz Interrupts simulated by fallback timer
30	xxxxxxxxxxxxxxxx	SBP_CNT	SBP Fill counter
31	xxxxxxxxxxxxxxxx	HK_CNT	Queued housekeeping blocks

3.1.9 Housekeeping Test Pattern

To enable verification of the X- and S-band channels, a simple test pattern - incrementing ramp -is available.

Word	Mask	Mnemonic	Parameter
0	0000000000001110	SOH_TYPE	Housekeeping Test Pattern
1	xxxxxxxxxxxxxxxxxxx	SOH_CRC	Cyclic Redundancy Check
2	xxxxxxxxxxxxxxxxxxx	SOH_TIME14	Time-stamp of the last update of this data packet
3-31	xxxxxxxxxxxxxxxxxxx	HTP_DATA	Each word is the previous HTP_DATA word + 0x0001

3.1.10 Spacecraft Time and Attitude Parameters

This packet provides time and attitude data for ground processing. Data received by SMEI from the spacecraft containing spacecraft time and attitude data is made available here. Note that words 2 and 3 from the data received by SMEI from the spacecraft are reversed in this housekeeping block.

Word	Mask	Mnemonic	Parameter
0	0000000000001111	SOH_TYPE	Time and Attitude Parameters
1	xxxxxxxxxxxxxxxxxxx	SOH_CRC	Cyclic Redundancy Check
2	xxxxxxxxxxxxxxxxxxx	SOH_TIME15	ICD Figure C6-3, word 3 (SCT Seconds LSW)
3	xxxxxxxxxxxxxxxxxxx	SCT_MSW	ICD Figure C6-3, word 2 (SCT Seconds MSW)
4	xxxxxxxxxxxxxxxxxxx	SCT_SSEC	ICD Figure C6-3, word 4
5	xxxxxxxxxxxxxxxxxxx	FQ_Q1_MSW	ICD Figure C6-3, word 5
6	xxxxxxxxxxxxxxxxxxx	FQ_Q1_LSW	ICD Figure C6-3, word 6
7	xxxxxxxxxxxxxxxxxxx	FQ_Q2_MSW	ICD Figure C6-3, word 7
8	xxxxxxxxxxxxxxxxxxx	FQ_Q2_LSW	ICD Figure C6-3, word 8
9	xxxxxxxxxxxxxxxxxxx	FQ_Q3_MSW	ICD Figure C6-3, word 9
10	xxxxxxxxxxxxxxxxxxx	FQ_Q3_LSW	ICD Figure C6-3, word 10
11	xxxxxxxxxxxxxxxxxxx	FQ_Q4_MSW	ICD Figure C6-3, word 11
12	xxxxxxxxxxxxxxxxxxx	FQ_Q4_LSW	ICD Figure C6-3, word 12
13	xxxxxxxxxxxxxxxxxxx	IBE_X_MSW	ICD Figure C6-3, word 13
14	xxxxxxxxxxxxxxxxxxx	IBE_X_LSW	ICD Figure C6-3, word 14
15	xxxxxxxxxxxxxxxxxxx	IBE_Y_MSW	ICD Figure C6-3, word 15
16	xxxxxxxxxxxxxxxxxxx	IBE_Y_LSW	ICD Figure C6-3, word 16
17	xxxxxxxxxxxxxxxxxxx	IBE_Z_MSW	ICD Figure C6-3, word 17
18	xxxxxxxxxxxxxxxxxxx	IBE_Z_LSW	ICD Figure C6-3, word 18
19	xxxxxxxxxxxxxxxxxxx	TWM_X_MSW	ICD Figure C6-3, word 19
20	xxxxxxxxxxxxxxxxxxx	TWM_X_LSW	ICD Figure C6-3, word 20
21	xxxxxxxxxxxxxxxxxxx	TWM_Y_MSW	ICD Figure C6-3, word 21
22	xxxxxxxxxxxxxxxxxxx	TWM_Y_LSW	ICD Figure C6-3, word 22
23	xxxxxxxxxxxxxxxxxxx	TWM_Z_MSW	ICD Figure C6-3, word 23
24	xxxxxxxxxxxxxxxxxxx	TWM_Z_LSW	ICD Figure C6-3, word 24
25	xxxxxxxxxxxxxxxxxxx	SL_X_MSW	ICD Figure C6-3, word 25
26	xxxxxxxxxxxxxxxxxxx	SL_X_LSW	ICD Figure C6-3, word 26
27	xxxxxxxxxxxxxxxxxxx	SL_Y_MSW	ICD Figure C6-3, word 27
28	xxxxxxxxxxxxxxxxxxx	SL_Y_LSW	ICD Figure C6-3, word 28
29	xxxxxxxxxxxxxxxxxxx	SL_Z_MSW	ICD Figure C6-3, word 29
30	xxxxxxxxxxxxxxxxxxx	SL_Z_LSW	ICD Figure C6-3, word 30
31	xxxxxxxx- - - - -	ATT_SEQ	ICD Figure C6-3, word 0, LSB
31	- - - - - xxxxxxxx		ICD Figure C6-3, word 31, LSB

3.1.11 Reserved Blocks

These blocks are reserved for further SoH parameters, should they be needed. They have the same basic header structure as other SoH packets.

Word	Mask	Mnemonic	Parameter
0	xxxxxxxxxxxxxxxxxxx	SOH_TYPE	Reserved Blocks
	0000000000000001		Spare
	0000000000000010		Spare
	0000000000000011		Spare
	xxxxxxxxxxxxx0000		Spare
1	xxxxxxxxxxxxxxxxxxx	SOH_CRC	Cyclic Redundancy Check

3.2 Science Data Stream

The science data stream is created by multiplexing image data and state of health data. A small header is used to delineate the different data types, and to allow the data processing software to resynchronise after a loss of telemetry. We define a synchronisation header, plus all the data until the next synchronisation header as a 'chunk'. Each chunk has a maximum size of 8192 words.

When embedding state of health information into the science data stream, the packet formats are identical to those used in the state of health data stream. These formats are defined in sections 3.1.1 to 3.1.11. A state of health chunk may hold one or more state of health packets.

When embedding camera image data into the science data stream, a complete frame from one camera is transmitted, in one or more back-to-back chunks containing image data packets. Immediately following the image data chunk(s), a chunk containing the camera observation parameter packet (section 3.1.1) is inserted into the datastream.

The figure to the right shows a sample data stream. In this example, a complete image (fitting completely into a single chunk) is followed by a set of observation parameter housekeeping data in chunk 2. The timestamp on the observation housekeeping indicates the time at which the frame was started. This can be used to correlate the frame against spacecraft attitude information. The next chunk (3) can contain either image data, or more state of health data, and so on.

Sync Header (Chunk 1)
Image Data
Image Data
Image Data
Image Data
Sync Header (Chunk 2)
SoH Data (Obs Params)
Sync Header (Chunk 3)
SoH Data
Sync Header (Chunk 4)

3.2.1 Science Data Stream Synchronisation Header

This is the simple header used to separate the science data stream into image and state of health data. A synchronisation word provides a mechanism to locate the header, and the size field allows rapid location of the next header in the data stream (and also verification that the synchronisation word located was not a false-positive).

When the header is followed by camera image data for a new image, the SH_TYPE field contains 0, and the SH_CAM field is used to identify which camera image data is from. If there are too many image data packets to fit into a single 8192 word chunk, a new synchronisation header is inserted into the stream, with the SH_CAM field holding the image data continuation marker (00), and with SH_TYPE containing 0.

When the header is followed by state of health data, the SH_TYPE field is 1, and the SH_CAM field is 00.

Word	Mask	Mnemonic	Parameter
0	xxxxxxxxxxxxxxxxxxxx	SH_SYNC	Synchronisation Pattern
1	- - -xxxxxxxxxxxxxxxx	SH_SIZE	Number of words until the next header
1	-xx-----	SH_CAM	Camera Identifier or Continuation indicator
	-00-----		Image Data Continuation Marker / State of Health
	-01-----		Camera 1
	-10-----		Camera 2
	-11-----		Camera 3
1	x-----	SH_TYPE	Image or Housekeeping indicator
	0-----		Image Data
	1-----		State of Health Data

3.2.2 Image Data Packet Format

Each frame of camera image data is buffered in memory until the entire frame has been processed. The image data is formatted into 264 word packets - 8 words of error correction code, followed by 256 words of (optionally rice compressed) image data.

Word	Mask	Mnemonic	Parameter
0	xxxxxxxxxxxxxxxxxxxx	IDP_ECC0	Error correction data
1	xxxxxxxxxxxxxxxxxxxx	IDP_ECC1	Error correction data
2	xxxxxxxxxxxxxxxxxxxx	IDP_ECC2	Error correction data
3	xxxxxxxxxxxxxxxxxxxx	IDP_ECC3	Error correction data
4	xxxxxxxxxxxxxxxxxxxx	IDP_ECC4	Error correction data
5	xxxxxxxxxxxxxxxxxxxx	IDP_ECC5	Error correction data
6	xxxxxxxxxxxxxxxxxxxx	IDP_ECC6	Error correction data

7 xxxxxxxxxxxxxxxxxxxx IDP_ECC7 Error correction data
 8-263 xxxxxxxxxxxxxxxxxxxx IDP_DATA Image data.

It is usual for the image data not to fit exactly into a whole number of 256 word packets. When the final packet of an image is filled with data, the remaining words of the packet are padded out with zeros when calculating the error correction codes.

This zero padding is *not transmitted* in the science data stream. The final image data packet for a frame of camera data is truncated. The length of this packet is derived by examining the SH_SIZE field of the preceding synchronisation header. For image data, the field contains (264 * full packets) + (size of last packet). There are always 8 words of error correction code.

The error correction code used here is a rectangular coding scheme. The diagram below shows the correspondence between the compressed image data, and the error correction words. IDP_ECC0-3 are calculated by a simple xor operation down each column. IDP_ECC4-7 are calculated from the parity bit for each row of the table. Further details are in Appendix A.

Word 0	Word 1	Word 2	Word 3	IDP_ECC4
.	.	.	.	
Word 60	Word 61	Word 62	Word 63	IDP_ECC5
Word 64	Word 65	Word 66	Word 67	
.	.	.	.	IDP_ECC6
Word 124	Word 125	Word 126	Word 127	
Word 128	Word 129	Word 130	Word 131	IDP_ECC7
.	.	.	.	
Word 188	Word 189	Word 190	Word 191	IDP_ECC0
Word 192	Word 193	Word 194	Word 195	
.	.	.	.	IDP_ECC1
Word 252	Word 253	Word 254	Word 255	
IDP_ECC0	IDP_ECC1	IDP_ECC2	IDP_ECC3	

A. Rectangular Error Correction Coding

Rectangular error correction codes work by arranging the data into an array of $m \times n$ bits. For each row and column of the array, a parity bit is generated, and these parity bits are included in the data transmitted. For each encoded packet, rectangular encoding can detect and correct single bit errors, and also detect all dual bit errors, and a number of other bit error patterns.

Decoding single bit errors requires each row and column be parity checked. The incorrect bit is located by cross-referencing the row and column for which the parity check failed.

A.1 SMEI Conventions

For image data, we chose to use an array of $64 \times N$ bits for generating the error correction codes.

The final part of an image may not completely fill a $64 \times N$ array, and so to avoid wasting bandwidth, the final array is transmitted as a $64 \times Q$ array, with Q varying as needed. The error correction code generation is performed as if the $64 \times Q$ block was $64 \times N$, with the unused words filled with zero.

The bit error rate of 10^{-6} specified in the ICD for data received at the ground station determines the rate at which we expect to receive image data which cannot be corrected. The following table shows a range of results for rectangular encoding.

Downlink BER	100E-08	$P(\text{error per block}) = [P(\text{downlink}) * \text{Total Block Bits}]^{\text{Errors Per Block}}$
Frame Size	63200 Bits	$P(\text{error per frame}) = P(\text{error per block}) * \text{Data Blocks Per Frame}$
Assumes	2:1	Overhead = ECC bits / Data bits
Compression		

	RECT 64x16bit	RECT 64x32bit	RECT 64x64bit	RECT 64x128bit
Block Data Bits	1024	2048	4096	8192
Block Data Bytes	128	256	512	1024
ECC Bits	80	96	128	192
Overhead	7.81%	4.69%	3.13%	2.34%

Errors/block	P(error)	1/P(error)	P(error)	1/P(error)	P(error)	1/P(error)	P(error)	1/P(error)
1	1.1E-03	906	2.1E-03	466	4.2E-03	237	8.4E-03	119
2	1.2E-06	820468	4.6E-06	217546	1.8E-05	56047	7.0E-05	14226
3	1.3E-09	743177889	9.9E-09	101467196	7.5E-08	13268697	5.9E-07	1696861

Errors/frame	P(error)	1/P(error)	P(error)	1/P(error)	P(error)	1/P(error)	P(error)	1/P(error)
1	6.8E-02	15	6.6E-02	15	6.5E-02	15	6.5E-02	15

We select N to be 64, as this gives a good trade-off between the overhead of the correction codes (3.2%), and the mean time between dual-bit errors.

If we assume a compression ratio of 2:1 for science image data, then in normal observation mode we expect to see one image in 3,600 with an image data packet containing a dual-bit error, or approximately one frame every 80 minutes.

For $N = 64$, there are 8 words of error correction data for every 256 words of compressed image data. In the image data packet (section 3.2.2), we define the error correction words as IDP_ECC0 to IDP_ECC7. They are calculated as follows:

- IDP_ECC0 Xor data words 0, 4, 8, ($w^4 + 0$), 252.
- IDP_ECC1 Xor data words 1, 5, 9, ($w^4 + 1$), 253.
- IDP_ECC2 Xor data words 2, 6, 10, ($w^4 + 2$), 254.
- IDP_ECC3 Xor data words 3, 7, 11, ($w^4 + 3$), 255.
- IDP_ECC4 Bit b generated from parity bit for data words (b^4) to ($b^4 + 3$).
- IDP_ECC5 Bit b generated from parity bit for data words ($b^4 + 64$) to ($b^4 + 67$).
- IDP_ECC6 Bit b generated from parity bit for data words ($b^4 + 128$) to ($b^4 + 131$).
- IDP_ECC7 Bit b generated from parity bit for data words ($b^4 + 192$) to ($b^4 + 195$).

B. Housekeeping Checksum Coding

The checksum coding used for SMEI housekeeping blocks is the same as used by WindSat. The code is generated using the standard 16-bit SDLC CRC algorithm, as defined in 'Numerical Recipes in C, Second Edition'.

Numerical Recipes in C, 2nd Edition is available on the web.

- [Publisher's Site](http://www.nr.com/) <http://www.nr.com/>
- Los Alamos <http://lib-www.lanl.gov/numerical/index.html>
- Universal Library http://www.ulib.org/webRoot/Books/Numerical_Recipes/

It should be noted that in the example software on page 901 for calculating the CRC is incorrect.

Correct C code:

```
for (j = 0; j < len; j++)      Main loop over the characters in the array.
```

not,

```
for (j = 1; j <= len; j++)    Main loop over the characters in the array.
```

C. Rice Compression Coding

The compression scheme used for SMEI image data is the Rice Compression Scheme. This scheme extracts the noise bits from the data, and sends these bits 'as-is'. The remainder of the word is transmitted using difference-encoding, with special codes used for extreme jumps in value. Rice compression is a lossless algorithm.

The scheme used is based on that documented in a paper by Michael W. Richmond and Nancy E. Ellman, titled 'Another Technique for Compressing Astronomical Imaging'. That paper and sample source code is available on the web.

- Original Paper <http://stupendous.isc.rit.edu/richmond/rice/>
- Birmingham copy <http://www.sr.bham.ac.uk/~mpc/p2/smei/ricepaper/>

Note that there have been many compression schemes produced by Rice et al. The code used during SMEI software development to decode images, and reference images are available on the web.

- SMEI Library <http://www.sr.bham.ac.uk/~mpc/p2/smei/compression/>

D. Analogue Monitor Calibration Tables

There are 24 analogue monitors on SMEI, as defined in the following table.

<i>Amon</i>	<i>Function</i>	<i>Sensor</i>	<i>Approximate Range</i>	
0	Instrument Current	Linear	0.03A	3.14A
1	Processor PCB 5V	Linear	3.56v	6.34v
2	Processor PCB Temperature	YSI 44004	75.5C	-32.8C
3	DHU Power Supply Temperature	YSI 44004	75.5C	-32.8C
4	Spare			
5	Processor PCB Current	Linear	0.03A	1.45A
6	Camera 1 Radiator Temperature	YSI 44003A	46.8C	-64.1C
7	Camera 1 CCD Temperature	YSI 44003A	46.8C	-64.1C
8	Camera 1 Electronics Temperature	YSI 44004	75.5C	-32.8C
9	Camera 1 Mirror Temperature	YSI 44004	75.5C	-32.8C
10	Camera 1 Baffle Temperature	YSI 44003A	46.8C	-64.1C
11	Camera 1 Spare			
12	Camera 2 Radiator Temperature	YSI 44003A	46.8C	-64.1C
13	Camera 2 CCD Temperature	YSI 44003A	46.8C	-64.1C/ home/mpc/ www_html/ pulsar/sm ei.old/ricep aper
14	Camera 2 Electronics Temperature	YSI 44004	75.5C	-32.8C
15	Camera 2 Mirror Temperature	YSI 44004	75.5C	-32.8C
16	Camera 2 Baffle Temperature	YSI 44003A	46.8C	-64.1C
17	Camera 2 Spare			
18	Camera 3 Radiator Temperature	YSI 44003A	46.8C	-64.1C
19	Camera 3 CCD Temperature	YSI 44003A	46.8C	-64.1C
20	Camera 3 Electronics Temperature	YSI 44004	75.5C	-32.8C
21	Camera 3 Mirror Temperature	YSI 44004	75.5C	-32.8C
22	Camera 3 Baffle Temperature	YSI 44003A	75.5C	-32.8C
23	Camera 3 Spare			

The physical response of the thermistors used in the monitors was modelled using a polynomial fit:

$$X = C0 + C1*(N) + C2*(N**2) + C3*(N**3) + C4*(N**4) + C5*(N**5)$$

where

	SMEI (I)	PROC (V)	PROC (I)	YSI44003A	YSI44004
C0	3.100E-02	3.560E+00	2.500E-02	4.6845E+01	7.5525E+01
C1	1.220E-02	1.090E-02	5.570E-03	-1.0766E+00	-8.5894E-01
C2	-	-	-	1.1324E-02	8.2167E-03